

Model PR2V-4



Control up to 4 PCs or File Servers from One Station



FEATURES

- Works with all VGA Monitor Types
- Convenient Desktop Size
- Embedded Mouse Translation for Serial Mouse
- On-Screen Display Control (Optional)



DESCRIPTION

The Easiest, Most 'Personal' Computer Switch Yet

The Model PR2V-4 allows you to control and operate up to four PCs directly from your desktop. With no software to install or boards to configure, the Personal Commander II is the easiest way to control multiple computers without ever leaving your desk. Attached computers can be up to 30 feet away for maximum flexibility in your workspace.

Use any Attached PC Just as if you Were Sitting in Front of it

All you need to do is select the PC you want to work on from the push-buttons on the Commander unit or through a simple keyboard sequence. Press enter, and you're there. It's that easy. An optional on-screen menuing system lets you name your computers, then select the desired PC from an easy to use menu.

Keep Alive Feature Protects your System in an Emergency

The Keep Alive feature allows the attached PCs to power the Commander in the event of a power failure on the Personal Commander II. Keeping the system powered up in an emergency ensures continued emulation and keeps you from losing valuable time and data.

Automatic Computer Channel Scanning

The Commander's built-in scanning feature lets you scan through your attached computers sequentially without user intervention. The length of time each channel remains on the screen is configurable and can be changed at any time.

The System

A Personal Commander II system consists of a Personal Commander II Unit (either Model PR2-4 or PR2V-4) and a 6, 8, 15, or 30-foot cable assembly for each attached computer (Model CUFC-x). The cables are universal supporting both Serial / PS/2 mouse and 5-pin / PS/2 keyboard on the attached computers. The Personal Commander II requires a PS/2 mouse and keyboard. For compatibility with your installed equipment, the Personal Commander II features an embedded mouse translation capability. Operated through the Personal Commander II, your PS/2 mouse will work with any attached PC or server regardless of whether the computer has a PS/2 or serial mouse.

Peripherals are powered by a built-in power supply which automatically adjusts to the line voltages and frequencies encountered internationally. The Personal Commander II can be recognized without being powered down. To reinitialize a channel, simply reboot the attached server, or use a front panel push-button.

SPECIFICATIONS

Number of Channels

4

Supported Hardware

Computer: PC/AT, PS/2 and 100% compatible
Video Modes: VGA, SVGA
Maximum Resolution: 1280 x 1024 @ 60Hz
Peripherals: PS/2 keyboard & mouse

Mouse Compatibility

IBM PS/2 Style
Kensington
Logitech Mouseman (PS/2)
Logitech Trackman
Microsoft Serial-PS/2 mouse
(Others might work, but these are known to be compatible)

Operating Voltage

100 to 240VAC

Power Frequency

50 to 60Hz

Input Power

8 Watts

Temperature

Operating: 5°C to 40°C
Storage: -20°C to 50°C

Size

Height: 1.7" (43.2mm)
Width: 10.8" (274.3mm)
Depth: 8.5" (215.9mm)

Agency Approvals

UL 1950
CSA C22.2 No. 950
EN 60950
EN 55022
EN 50082
FCC Part 15A

ORDERING GUIDE

Model PR2-4

Standard unit, no on-screen display, manual, power cord

Model PR2V-4

On-Screen Display unit, manual, power cord

CABLES

Model CUFC-6

6 ft cable

Model CUFC-8

8 ft cable

Model CUFC-15

15 ft cable

Model CUFC-30

30 ft cable



INDUSTRIAL COMPUTER SOURCE®

6260 Sequence Drive, San Diego, CA 92121

1-800-523-2320

<http://www.indcomsrc.com>